



Expertise, variety and quality



www.atrinelec.com

02166766957 - 02166766927



تهران پاسار امجد طبقه 1 واحد 16



info@atrinelec.com



@atrinelec



ELC-131D & ELC-3131D Specifications

ELC-3131D	ELC-131D			
Features Include:				
Full autorange, two major measuring methods: parallel and series, 2W/4W selections (ELC-3131D only). two selected frequencies, max/min/avg record, D/Q factor test mode, relative mode, calibration, tolerance mode, auto power off (ELC-131D only).				
Parameters Measurement:				
L, C, R, and D/Q				
Measurement Circuit Mode:				
1) Capacitance/Resistance Measurement-Defaults to parallel mode for all ranges. 2) Inductance Measurement-Defaults to series mode for all ranges. Both parallel and series mode data are available through simple key operation.				
Display:				
L/C/R: maximum 9999 display except at 10mF (120Hz) and 1mF (1kHz) measurement ranges which have max 1999 display D/Q: 3 digits, maximum 999 display (AUTO RANGE)				
Ranging Mode:				
Auto & manual				
Test Frequency:				
1kHz & 120Hz				
Measurement Rate:				
1 measurement/second, normal				
Response Time:				
1 second/DUT (device under test) @ manual range				
Power Requirement:				
AC 100/120/220/240V 50/60Hz	(1) DC 9V battery (2) External DC Adaptor-DC12V (MIN)-15V (MAX) (load: 50mA min)			
Size:				
26 (W) x 21 (L) x 7 (H) cm; 1.4kg approx.	90 (W) x 192 (L) x 37 (H) mm; 390 grams			
Standard Accessories: Test alligator clips (2 pair), Power cord, square fuse (0.1A or 0.2A AC fast-blow), manual				
Standard Accessories: Test alligator clips, battery, manual Optional Accessories: Holster, DC 12V power adaptor				
Resistance				
RANGE: 10MΩ, 1MΩ, 100kΩ, 10kΩ, 1kΩ, 100Ω, 10Ω				
Accuracy:				
@ 10MΩ ± (0.6% + 5 digits)	1kHz only	@ 10MΩ ± (2.0% + 8 digits)	1kHz only	
@ 1MΩ ± (0.3% + 3 digits)		@ 1MΩ ± (0.5% + 5 digits)		
@ 100kΩ ± (0.3% + 2 digits)		@ 100kΩ ± (0.5% + 3 digits)		
@ 10kΩ ± (0.3% + 2 digits)		@ 10kΩ ± (0.5% + 3 digits)		
@ 1kΩ ± (0.3% + 2 digits)		@ 1kΩ ± (0.5% + 3 digits)		
@ 100Ω ± (0.5% + 3 digits)		@ 100MΩ ± (0.5% + 5 digits)		
@ 10Ω ± (0.6% + 5 digits)		@ 10Ω ± (1.2% + 8 digits)		
Inductance				
Test Frequency: 120Hz/1kHz (DF < 0.5)				
RANGE: 10000H, 1000H, 100H, 10H, 1H, 100mH, 10mH, 1mH				
Accuracy:				
@ 10000H ± (0.3% + (Lx/10000)% + 5 digits)	1kHz only	@ 10000H Accuracy not specified	120Hz only	
@ 1000H ± (0.3% + (Lx/10000)% + 5 digits)		@ 1000H ± (1.0% + (Lx/10000)% + 5 digits)	120Hz only	
@ 100H ± (0.3% + (Lx/10000)% + 5 digits)		@ 100H ± (0.7% + (Lx/10000)% + 5 digits)	120Hz	
@ 10H ± (0.3% + (Lx/10000)% + 5 digits)		@ 10H ± (1.0% + (Lx/10000)% + 5 digits)	1kHz	
@ 1H ± (0.3% + (Lx/10000)% + 5 digits)		@ 1H ± (0.7% + (Lx/10000)% + 5 digits)		
@ 100mH ± (0.3% + (Lx/10000)% + 5 digits)		@ 100mH ± (1.0% + (Lx/10000)% + 5 digits)	120Hz	
@ 10mH ± (0.3% + (Lx/10000)% + 5 digits)		@ 10mH ± (0.7% + (Lx/10000)% + 5 digits)	1kHz	
@ 1mH ± (0.3% + (Lx/10000)% + 5 digits)	1kHz only	@ 1mH ± (2.0% + (Lx/10000)% + 5 digits)	120Hz	
			± (1.2% + (Lx/10000)% + 5 digits)	1kHz
			± (2.0% + (Lx/10000)% + 5 digits)	1kHz only
Capacitance				
RANGE: 10MF, 1000μF, 100μF, 10μF, 1000nF, 100nF, 10nF, 1nF				
Accuracy:				
@ 10mF ± (2.5% + 5 digits) (DF < 0.1)	120Hz only	@ 10mF ± (5.0% + 5 digits) (DF < 0.1)	120Hz only	
@ 1000μF ± (0.6% + 5 digits) (DF < 0.1)	120Hz	@ 1000μF ± (1.0% + 5 digits) (DF < 0.1)	120Hz	
@ 1mF ± (2.5% + 5 digits) (DF < 0.1)	1kHz	@ 1mF ± (5.0% + 5 digits) (DF < 0.1)	1kHz	
@ 100μF ± (0.4% + 3 digits) (DF < 0.5)	120Hz	@ 100μF ± (0.7% + 3 digits) (DF < 0.5)	120Hz	
	± (0.6% + 5 digits) (DF < 0.1)	1kHz	± (1.0% + 5 digits) (DF < 0.1)	1kHz
@ 10μF ± (0.4% + 3 digits) (DF < 0.5)	120Hz	@ 10μF ± (0.7% + 3 digits) (DF < 0.5)		
	± (0.4% + 3 digits) (DF < 0.5)	1kHz	± (0.7% + 3 digits) (DF < 0.5)	
@ 100nF ± (0.4% + 3 digits) (DF < 0.5)	120Hz	@ 100nF ± (0.7% + 3 digits) (DF < 0.5)		
	± (0.4% + 3 digits) (DF < 0.5)	1Hz	± (0.7% + 3 digits) (DF < 0.5)	
@ 1000nF ± (0.4% + 5 digits) (DF < 0.5)	120Hz	@ 1000nF ± (1.0% + 5 digits) (DF < 0.1)	120Hz	
	± (0.4% + 5 digits) (DF < 0.5)	1kHz	± (0.7% + 5 digits) (DF < 0.5)	1kHz
@ 10nF ± (0.6% + 5 digits) (DF < 0.1)	120Hz	@ 10nF ± (1.0% + 5 digits) (DF < 0.1)	120Hz	
	± (0.4% + 5 digits) (DF < 0.5)	1kHz	± (0.7% + 5 digits) (DF < 0.5)	1kHz
@ 100pF ± (0.6% + 5 digits) (DF < 0.1)	1kHz only	@ 1000pF ± (1.0% + 5 digits) (DF < 0.1)	1kHz only	